



MAG2P

2 Zone Fire Panel

- 2 programmable zones
- Active end of line monitoring and head removal
- 30 fire detectors per zone
- Unlimited number of call points per zone
- Integral sound alarm button
- 'Class change' facility
- Enable/disable security key
- One man walk test facility
- Volt free fire change over relay
- Volt free fault change over relay
- Individual sounder circuit fault ID
- Individual zone/sounder isolate
- CE certified to EN54 P2/4
- Requires only 1x12v battery
- MAG2P - ABS casing



Inputs

Max Detectors Per Zone	30
Thresholds for Zone Conditions	0 - 2 mA (Fault condition) 2 - 6 mA (Normal condition) 6 - 110 mA (Fire condition) 110 mA - Short (Fault condition)

Power

Mains Fail Consumption	50mA
Mains Supply	230 VAC $\pm$ 10%
Standby Supply	1 x 7ah 12V S.L.A. Battery
Power Availability	0.7 amps

Outputs

Sounder 1	24V (max 300mA fused)
Sounder 2	24V (max 300mA fused)
Fault/Fire Relay	Volt free 500mA @ 24V (max load)
Auxiliary Output	24VDC (300mA fused)

Environment

Working Temperature	0 to 40°C
Storage Temperature	-20 to 60°C
Humidity	0 - 95%
Dimensions MAG2P	340 x 290 x 100mm
Dimensions MAG2	200 x 290 x 80mm
Weight	MAG2P - 2.1Kg MAG2 - 2.7Kg



MAG2

2 Zone Fire Panel - Metal Casing

MAGBAR2/4

Spare Barrel & key for use with MAG 2 & 4

