



MAGPRO96

Addressable 96 Zone Fire Panel

- 96 Zones
- Maximum 250 devices per loop
- Memory Log: 10,000 events
- Networkable up to 32 Panels
- 320 x 240 pixel touch screen display
- Free programming software
- Micro USB port for PC connection
- Loop & battery calculator software included
- Certified to EN54-2/4

96 zone addressable fire alarm panel supplied with 1 loop. Expandable to 4 loops using additional MAGPRO96-L250's. A maximum of 250 devices can be connected to each loop.

Inputs

Loops	1 expandable to 4
Devices Per Loop	250
Protocol	MAGPRO

Power

Mains Fail Consumption	285mA DC - 1 LOOP 360mA DC - 2 LOOP 435mA DC - 3 LOOP 510mA DC - 4 LOOP
Mains Supply	230V AC + - 10%
Max Loop Current	500mA DC
Backup	1x12V 17Ah

Outputs

1 Sounder	24v DC @ 300mA
4 Programmable Relays	110v AC @ 1A
2 Monitored Outputs	24v DC @ 300mA
1 Auxiliary Output	24v DC @ 300mA
1 Fault Output	24v DC @ 300mA

Environment

Working Temperature	-5C TO +40C
Storage	-10C TO 60C
Humidity	0 - 95%
Weight	4.2KG
Dimensions	456 x 350 x 125mm



MAGPRO96-L250
Single Loop Expander for 250 Devices



MAGPRO-PROG PROGRAMMING TOOL
For best installation practise see page 58