



# ADDRESSABLE FIRE PANELS




## MAGPRO16

Addressable 16 Zone Fire Panel



16 zone addressable fire alarm panel supplied with 1 loop.  
Expandable to 2 loops using MAGPRO16-L250.  
A maximum of 250 devices can be connected to each loop.

- 16 Zones
- Maximum 250 devices per loop
- Memory Log: 10,000 events
- Networkable up to 32 Panels
- 4 x 40 character LCD display
- Free programming software
- Micro USB port for PC connection
- Loop & battery calculator software included
- Certified to EN54-2/4



### MAGPRO16-L250

Single Loop Expander 250 Devices



INPUTS	Loops	1 expandable to 2
	Devices Per Loop	250
	Protocol	MAGPRO
POWER	Mains Fail Consumption	125mA DC – 1 LOOP 213mA DC – 2 LOOP
	Mains Supply	230V AC + - 10%
	Max Loop Current	500mA DC
	Backup	1x12V 17Ah

OUTPUTS	2 Sounders	24v DC @ 500mA
	4 Programmable Relays	24v DC @ 100mA
	3 Monitored Outputs	24v DC @ 100mA
	3 Monitored Inputs	Volt free contacts
ENVIRONMENT	Working Temperature	-5C TO +40C
	Storage	-10C TO 60C
	Humidity	0 - 95%
	Weight	3.6KG
	Dimensions	320 x 220 x 80mm