



MAGPRO96

Addressable 96 Zone Fire Panel



96 zone addressable fire alarm panel supplied with 1 loop.
Expandable to 4 loops using additional MAGPRO96-L250's.
A maximum of 250 devices can be connected to each loop.

- 96 Zones
- Maximum 250 devices per loop
- Memory Log: 10,000 events
- Networkable up to 32 Panels
- 320 x 240 pixel touch screen display
- Free programming software
- Micro USB port for PC connection
- Loop & battery calculator software included
- Certified to EN54-2/4



MAGPRO96-L250
Single Loop Expander 250 Devices



INPUTS	Loops	1 expandable to 4
	Devices Per Loop	250
	Protocol	MAGPRO
POWER	Mains Fail Consumption	285mA DC - 1 LOOP 360mA DC - 2 LOOP 435mA DC - 3 LOOP 510mA DC - 4 LOOP
	Mains Supply	230V AC + - 10%
	Max Loop Current	500mA DC
	Backup	1x12V 17Ah

OUTPUTS	1 Sounder	24v DC @ 300mA
	4 Programmable Relays	110v ac @ 1A
	2 Monitored Outputs	24v DC @ 300mA
	1 Auxillary Output	24v DC @ 300mA
	1 Fault Output	24v DC @ 300mA
ENVIRONMENT	Working Temperature	-5C TO +40C
	Storage	-10C TO 60C
	Humidity	0 - 95%
	Weight	4.2KG
	Dimensions	456 x 350 x 125mm