

[Conventional Fire Systems](#)[Fire Alarm Ancillaries](#)[Remote LED Indicator](#)[◀ Back to Search results for "BF318" \(3 other results\)](#)

Remote LED Indicator

Part No. **BF318**

- A high-quality remote LED indicator specifically designed for use in fire alarm systems.
- Incorporates a high intensity, wide-angle red LED which is clearly visible from the front of the plate when active.
- Ideal for indicating the activation of hidden or out of-sight fire detectors, etc.
- Includes a white 'write on' area allowing installers to add equipment locations.
- Fits on standard UK 16mm flush or surface mount back boxes.



Technical Specifications



Activation current	1.3mA @ 6VDC (Min) to 10mA @ 30 VDC (Max) if using 0V & +30V connections; 25mA (Max) if using 0V & LED only connections
Connections	+30V Max; LED only; 0V (CONN1).
Product dimensions (mm)	85 W x 85 H x D 23mm (Can be mounted on a standard UK 25mm single gang flush or surface back box).
Construction & finish	White PVC plate; Light grey label.
IP Rating	IP40.
Weight	48g.
Operating conditions/temperature	-10°C to +60°C.

Dimensions & Mounting Information



Product dimensions:	85 W x 85 H x 15 D mm.
Back box requirements:	Mounts on a standard UK 16mm flush or surface mount back box

BIM/CAD Drawings



BF318 flush mounted BIM (RFA)

 Download

BF318 surface mounted BIM (RFA)

 Download

Documentation



BF318 Remote LED Instructions

DFU0318000 Rev 2

 Download (75.49k)

10 other products in the same category:



24V 5A Relay On A Plate



24V 5A Isolatable Relay On A Plate



Auxiliary Device Isolator Plate



4 Zone Sounder Circuit Extender Kit



24V Vibrating Pillow Pad



Single Gang Locking Jack Socket for BF363



Document/Key Box



**BS 5839-6 Hush Button
(XP95/Discovery protocol)**



**BS 5839-6 Hush Button
(Hochiki ESP protocol)**



**BS 5839-6 Hush Button,
Stainless Steel...**

CONTACT US

 C-TEC , Challenge Way, Wigan, WN5 0LD, UK Opening times: 08:30 - 17:00 GMT.

 **+44 (0) 1942 322744**

 sales@c-tec.co.uk
