

# Technical Information

MINI WIRED CHIMES	COLOUR	NUMBER OF TUNES	TUNE NAMES	BATTERIES	TRANSFORMERS	SOUND LEVEL dB@1m***	MAX POWER VA/W	
D846	Oakland	White	2	3 Note Gong	Chime: 3 x 1.5v LR6 (AA)	D753 or D780	75	2W
D142	Atlanta	White	1	Ding Dong	Chime: 4 x 1.5v LR6 (AA)	D753 or D780	75	8VA
D143	Denver	White	1	Ding Dong	Chime: 4 x 1.5v LR6 (AA)	D753 or D780	75	8VA

CHIMES, BELLS, BUZZERS AND KITS	VOLTAGE	SIGNAL 1	SIGNAL 2	BATTERIES	FRIEDLAND TRANSFORMER	MAX POWER VA/W	SOUND LEVEL dB@1m MAX.	SOUND FREQUENCY NOTE 1 Hz	SOUND FREQUENCY NOTE 2 Hz	
D107	Facet	6V DC/8V AC	2-Note		4 x R14/C	D753 or D780	6 W	80	740	587
D113	Surf	6V DC/8V AC	2-Note		4 x R14/C	D753 or D780	6 W	80	740	587
D117	Ding Dong	6V DC/8V AC	2-Note		4 x R14/C	D753 or D780	6 W	80	740	587
D230	Big Ben	6V DC/8V AC	2-Note	1-Note	4 x R14/C	D753 or D780	6 W	80	740	587
D239	Bandera	6V DC/8V AC	2-Note	1-Note	4 x R14/C	D753 or D780	6 W	80	740	587
D454	Warbler	6V DC/8V AC	Warbling	2-Note	4 x R14/C	D753 or D780	6 W	87	740	587
D182	Minibuzzer	8V AC	Buzzer		n/a	D753 or D780		90		
D422	Surf Kit	6V DC/8V AC	2-Note		4 x R14/C	D753 or D780	6 W	80	740	587
D424	Facet Kit	6V DC/8V AC	2-Note		4 x R14/C	D753 or D780	6 W	80	740	587
D792	Underdome	8V AC	Bell		n/a	D743 or D770		85		
D902	Bell-in-One	3V DC	Bell		2 x RD20/D	n/a		80		
D973	Bell Kit	3V DC	Bell		2 x R20/D	n/a		80		
D128	Hockey Chime	6V DC/8V AC	2-Note		4 x R14/C	D753 or D780	6 W	80	740	587

MAINS VOLTAGE CHIMES WITH BUILT-IN TRANSFORMERS	VOLTAGE	SIGNAL 1	MAX. POWER VA/W	SOUND LEVEL dB@1m MAX	SOUND FREQUENCY NOTE 1 Hz	SOUND FREQUENCY NOTE 2 Hz	
D3126	Festival (incl. Transformer)	220-240V AC 50Hz	2-Note	16 VA	80	740	587
D3230	Big Ben (incl. Transformer)	220-240V AC 50Hz	2-Note	16 VA	80	740	587