

Timers & switches

Touch timer

3



Illuminated Touch Timer
Timers & switches

Illuminated Touch Timer - Timers & switches

The Touch timer offers energy saving features at the lightest of touches. With the reliability of a fully electronic unit, with no mechanical moving parts, it has all the features of the Elkay push button timer unit with the additional benefit of a featherlight touch activation.

Variable timing selection and a backlit blue neon indicator ring are all part of this feature-packed device. It is also suitable for multi-way applications thanks to slave switch options with the 2 wire and 3 wire master devices.

Key Features

- 16A any load type 3 wire (Live, switch live and neutral required)
- Blue Locator ring
- Can be interlinked with any Elkay slave switches (Only one master per circuit)
- Fits into 25mm depth back boxes
- Requires Capacitor PFCC-1 for all types of low wattage loads and in particular LED lighting
- 5 - 7 m detection range
- 16 Timer settings from 2 mins to 2 hours

2235A-1

- 3 wire (Live, switch live and neutral required)

Typical applications:

- Suitable for lighting, heating, ventilation systems and contactor coils
- Suitable for use in any area where control will help reduce energy usage

360A-1

- 2 wire (Live and switch live only)
- A 24 hour uninterrupted supply is required
- No neutral required

Typical applications:

- Suitable for lighting only
- Suitable for use in any area where control will help reduce energy usage

360A-3

- 3 core - Live, switch live and trigger required to connect to master
- No neutral required
- Any number of slaves can be used in circuit and can also replace intermediate switches

Typical applications:

- Can only be used with the master switch when multiple switches are required

Illuminated Touch Timer - Technical specification

| Part No. | Type | Configuration | Finish | Rating | GID |
|------------|--------------------|-----------------------------|--------|----------|-----------------|
| 2235A-1*** | Touch Timer Master | 3 Wire | White | 16A-240V | 7TCA299010R0003 |
| 360A-1*** | Touch Timer Master | 2 Wire* (for lighting only) | White | 16A-240V | 7TCA299010R0016 |
| 360A-3 | Touch Slave | 3 Core** | White | 16A-240V | 7TCA299010R0018 |

*PFCC-1 Capacitor will often be required when switching certain types of load - see Section 3/15 for full details or contact Elkay Technical

Slaves must be used with illuminated range and connected with 3 Core cables to Master unit. *Slave unit required for multiway switching
See Technical Section 6/4 & 6/6 for wiring diagrams