



5
Year Warranty

Emergency
Product

Self-Test
Emergency

Earthed



Hole knockouts
on each side of fitting




LED EMERGENCY EXIT BOX SIGNS + SELF-TEST
OPTION

Low energy alternative to standard emergency exit signs - perfect for
office, commercial and industrial applications

- Steel construction • LED charge light • Facility for remote switching
- 3 hour maintained mode as standard which can also be configured for non maintained operation
- Diffuser on base: for added downward illumination of escape route
- Long life energy efficient LED light source eliminates lamp replacement cycle without compromising panel visibility distance
- Battery test button
- Battery - Ni-Cd 3.6V 1500Ah
- Battery 1 year warranty - Replacement battery code: EB4

SEEXIT3ML: Automatic testing in accordance with BS EN 62034



| Code | Version / Legend Set Included | Wattage | Lumens | Avg. Rated Life (Hrs) | IP Rating | Viewing Distance | MOM / OPQ |
|-----------|-------------------------------|---------|--------|-----------------------|-----------|------------------|-----------|
| EXIT3MLED | Signs Directive Down Arrow | 4W | 55 lm | 30,000 hrs | IP20 | 32m | 6 / 6 |
| SEEXIT3ML | Self Test / ISO 7010 Up Arrow | | | | | | |

| Accessories | | | |
|-----------------|-----------|--------------------|-----------|
| Signs Directive | ISO 7010 | Version | MOM / OPQ |
| EBLGDL | ISOEBLGDL | Left Arrow Legend | 1 / 100 |
| EBLGDR | ISOEBLGDR | Right Arrow Legend | |
| EBLGDU | ISOEBLGDU | Up Arrow Legend | |
| | ISOEBLGDD | Down Arrow Legend | |