

ILEMPK010



This compact, all-in-one Emergency Conversion Kit is suitable for Integral LED Edge-Lit Panels and LED Downlights for use in switchable Maintained mode. It will provide emergency lighting for 3 hours, or optionally for 1.5 hours at a higher output. It is simple to install and features an optional remote test button and LED indicator.

### Details

**Barcode:** 5055788227373

**Category:** Emergency

**Range Name:** Conversion Kit

**Product Type:** Emergency Conversion Kit

**Product Body Finish:** Matt white. End cap blue

**Market Segment:** Commercial indoor

**Finish:** Matt white. End cap blue

**Warranty (Years):** 3

**CE RoHS:** Yes

### Physical Data

**Product Length (mm):** 250

**Product Depth (mm):** 32

**Product Width (mm):** 60

**Product Weight (g):** 300

**Optic:** Polycarbonate diffuser

**Material:** PVC

**Construction:** Injection moulding

**Bulb or Luminaire Shape:** Rectangle

**Luminaire Fixing:** Surface mounted

**Placement / Application:** Indoor, Emergency Lighting

### Electrical Data

**Voltage Range (v):** 220-240

**Input Voltage (V):** 220-240

**Output Voltage (V):** 15-60

**Dimming:** Non-Dimmable

**Driver Included:** Yes

**Electric Current:** AC

**Emergency Type:** Non-Maintained

**LVD Certified:** Yes

[Portal.Integral-Led.Com](http://Portal.Integral-Led.Com)

## Light Data

**Lumens Range:** 1 to 100

**Frequency Range (Hz):** 50/60

## Environment

**LVD Certified:** Yes

**CE RoHS:** Yes

**IK Rating (Impact Protection):** IK08

**IP Rating (Ingress Protection):** IP20

**Lowest Operating Temperature (°C):** 0

**Maximum Operating Temperature (°C):** 50

## Packaging

**Package Weight (g):** 330

**Package Length (mm):** 255

**Package Width (mm):** 63

**Package Depth (mm):** 35