

EMERGENCY CONVERSION KIT IP20 2.5-5W 15-60V 3HR WITH REMOTE LED INDICATOR AND TEST BUTTON INTEGRAL

ILEMPK010



This compact, all-in-one Emergency Conversion Kit is suitable for Integral LED Edge-Lit Panels and LED Downlights for use in switchable Maintained mode. It will provide emergency lighting for 3 hours, or optionally for 1.5 hours at a higher output. It is simple to install and features an optional remote test button and LED indicator.

Details

Quick Order Code:	26708
Barcode:	5055788227373
Category:	Emergency
Range Name:	Conversion Kit
Product Type:	Emergency Conversion Kit
Product Body Finish:	Matt white. End cap blue
Market Segment:	Commercial indoor
Finish:	Matt white. End cap blue
Warranty (Years):	3
CE RoHS:	Yes

Physical Data

Product Length (mm):	250
Product Depth (mm):	32
Product Width (mm):	60
Product Weight (g):	300
Optic:	Polycarbonate diffuser
Material:	PVC
Construction:	Injection moulding
Bulb or Luminaire Shape:	Rectangle
Luminaire Fixing:	Surface mounted
Placement / Application:	Indoor, Emergency Lighting

Electrical Data

Input Voltage (V):	220-240
Output Voltage (V):	15-60
Dimming:	Non-Dimmable

Driver Included:	Yes
Electric Current:	AC
Emergency Type:	Non-Maintained
LVD Certified:	Yes

Light Data

Environment

LVD Certified:	Yes
CE RoHS:	Yes
IK Rating (Impact Protection):	IK08
IP Rating (Ingress Protection):	IP20
Lowest Operating Temperature (°C):	0
Maximum Operating Temperature (°C):	50

Packaging

Package Weight (g):	330
Package Length (mm):	255
Package Width (mm):	63
Package Depth (mm):	35