





Plugs
- screwless
- with screw terminals

3





Amp.	16	32
Poles	5	5
d	153	181
Øe	65	72
f	75	88
m	117	138
n	37	46
Øp	8/21	11/24

Phase inverters,
screw terminal connection,
with flexible cable entry,
IP 44 ▲





Amp.	16	32
Poles	5	5
d	131	155
Øe	65	73
f	75	88
m	112	133
n	37	46
Øp	7,5 - 14,5	10 - 19,5

Phase inverters,
screw terminal connection,
with trumpet gland,
IP 44 ▲





Amp.	16			32			63		
Poles	3	4	5	3	4	5	3	4	5
d	123	131	131	155	155	155	240	240	240
Øe	51	65	65	73	73	73	81	81	81
f	60	68	75	79	79	88	97	97	97
m	118	112	112	133	133	133	192	192	192
n	37	37	37	46	46	46	67	67	67
Øp	7,5-14,5	7,5-14,5	7,5-14,5	10-19,5	10-19,5	10-19,5	18-34,5	18-34,5	18-34,5

Plugs, screw terminal connection,
with trumpet gland,
IP 44 ▲



Amp.	16
Poles	3
d	126
m	110
n	37
u	72
Øp	7,5-14,5

Plugs, screw terminal connection,
with trumpet gland, IP 67 ●●





Amp.	16	16	32	32
Poles	4	5	3 / 4	5
d	150-161	150-161	174-183	174-183
Øe	Ø 65	Ø 65	Ø 72	Ø 72
m	111	111	127	127
n	36,5	36,5	45,5	45,5
Øu	Ø 81	Ø 89	Ø 95	Ø 100
Øp	7,5-18,5	7,5-18,5	10-22,5	10-22,5

Plugs, screw terminal connection,
with cable gland, IP 67 ●●

or

Plugs, screwless (SL) with insulation displacement connection,
with cable gland, IP 67 ●●



Amp.	63		
Poles	3	4	5
d	246	246	246
u	109	109	109
m	174	174	174
Øp	14-33	14-33	14-33

Plugs, screw terminal connection,
with cable gland, IP 67 ●●

Ampère	Poles	110 V 50 a. 60 Hz			230 V 50 a. 60 Hz			400 V 50 a. 60 Hz			500 V 50 a. 60 Hz			> 50 - 500 V 100 - 300 Hz			> 50 - 500 V over 300 - 500 Hz			
		3pole 4h	4pole 4h	5pole 4h	3pole 6h	4pole 9h	5pole 9h	3pole 9h	4pole 6h	5pole 6h	3pole 7h	4pole 7h	5pole 7h	3pole 10h	4pole 10h	5pole 10h	3pole 2h	4pole 2h	5pole 2h	



		Part numbers																	
16	5			210 PH														10	
16	5			210 PH Ni														10	
32	5			230 PH														10	
32	5			230 PH Ni														10	
16	5			211 PH														10	
16	5			211 PH Ni														10	
32	5			231 PH														10	
32	5			231 PH Ni														10	
16	3	211 304	211 306	211 309														10	
16	4	211 404	211 409	211 406	211 407	211 410	211 402											10	
16	5	211 504	211 509	211														10	
16	5			211 Ni														10	
32	3	231 304	231 306	231 309														10	
32	4	231 404	231 409	231 406	231 407	231 410	231 402											10	
32	5	231 504	231 509	231														10	
32	5			231 Ni														10	
63	3	261 304	261 306	261 309														5	
63	4	261 404	261 409	261 406	261 407	261 410	261 402											5	
63	5	261 504	261 509	261														5	
63	5			261 Ni														5	
16	3	219 304	219 306	219 309														10	
16	5			219 Ni														10	
32	5			239 Ni														10	
16	4	219 404	219 409	219 406	219 407	219 410	219 402											10	
16	5	219 504	219 509	219														10	
32	3	239 304	239 306	239 309														10	
32	4	239 404	239 409	239 406	239 407	239 410	239 402											10	
32	5	239 504	239 509	239														10	
<p>The plugs listed here are also available as screwless version with insulation displacement connection. To order a plug as screwless version, just add "SL" behind the part number.</p>																			
63	3	268 304	268 306	268 309														5	
63	4	268 404	268 409	268 406	268 407	268 410	268 402											5	
63	5	268 504	268 509	268														5	

Availability of blue printed (or not listed) frequencies and voltages up to 690 V on request!