



MS116 manual motor starters

Main accessories


2



PS1-2-0-65



PS1-3-1-100



S1-M1-25



S1-M2-25



SA1

Description

Three-phase busbars ensure a quick and safe connection and are therefore a cost effective solution. A variety of different three-phase busbars up to 100 A are in the assortment. Between 2 and 5 manual motor starters with none, one or two lateral auxiliary contacts can be connected. Different three-phase feeder terminals are available according to the application.

Ordering details

Rated operational current A	Number of MMS	Number of lateral aux.	Type	Order code		Pkg qty	Weight (1 pce) kg
Three-phase busbars							
65	2	0	PS1-2-0-65	1SAM201906R1102		10	0.034
65	3	0	PS1-3-0-65	1SAM201906R1103		10	0.055
65	4	0	PS1-4-0-65	1SAM201906R1104		10	0.077
65	5	0	PS1-5-0-65	1SAM201906R1105		10	0.098
65	2	1	PS1-2-1-65	1SAM201906R1112		10	0.036
65	3	1	PS1-3-1-65	1SAM201906R1113		10	0.060
65	4	1	PS1-4-1-65	1SAM201906R1114		10	0.087
65	5	1	PS1-5-1-65	1SAM201906R1115		10	0.108
65	2	2	PS1-2-2-65	1SAM201906R1122		10	0.040
65	3	2	PS1-3-2-65	1SAM201906R1123		10	0.067
65	4	2	PS1-4-2-65	1SAM201906R1124		10	0.095
65	5	2	PS1-5-2-65	1SAM201906R1125		10	0.122
100	3	0	PS1-3-0-100	1SAM201916R1103		10	0.084
100	4	0	PS1-4-0-100	1SAM201916R1104		10	0.117
100	5	0	PS1-5-0-100	1SAM201916R1105		10	0.154
100	3	1	PS1-3-1-100	1SAM201916R1113		10	0.094
100	4	1	PS1-4-1-100	1SAM201916R1114		10	0.134
100	5	1	PS1-5-1-100	1SAM201916R1115		10	0.172
100	3	2	PS1-3-2-100	1SAM201916R1123		10	0.105

Rated operational current A	Rated cross section mm ²	Mounting form	Type	Order code		Pkg qty	Weight (1 pce) kg
Three-phase feeder terminals							
65	25	Flat	S1-M1-25	1SAM201907R1101		10	0.038
65	25	High	S1-M2-25	1SAM201907R1102		10	0.051
65	25	UL type E and IEC	S1-M3-25	1SAM201907R1103		10	0.042
100	35	UL type E and IEC	S1-M3-35	1SAM201913R1103		10	0.060

Description	Type	Order code		Pkg qty	Weight (1 pce) kg
Protection cover for busbars	BS1-3	1SAM201908R1001		50	0.003
Lock handle	SA1	GJF1101903R0001		10	0.003
Padlock	SA2	GJF1101903R0002		10	0.020
Lock handle box SA1/SA2	SA3	GJF1101903R0003		10	0.050
Screw fixing kit	FS116	1SAM201909R1001		1	0.020