

# EMERGENCY LED

## DYNAMO 2W LED Non maintained Emergency Downlight

- Recessed
- 3 hour emergency operation
- 120° beam angle
- Non maintained
- Includes manual test button and LED indicator
- Adjustable trim enables compatibility with cut-out diameters of 72mm and 110mm

### R2WLEDNME-01

Total Power (W):	2
Total Light Output (lm):	190
CCT L100 (K):	7,000
CRI at L100:	75
Lux at 1m (lux):	25
Lifetime (hrs):	30,000
Depth (mm):	65
Diameter (mm):	130
Box Qty:	1
Weight (kg):	0.71
IP:	20

