# DATASHEET

## BATSCWEM6

### 230V 6ft 27/52W CCT Adjustable Emergency Batten

www.mlaccessories.co.uk




| MLA PART CODE | BATSCWEM6 |
|---|---|
| DESCRIPTION | 230V 6ft 27/52W CCT Adjustable Emergency Batten |
| NET WEIGHT (KG) | 1.99 |
| FINISH | White |
| DIFFUSER | Opal |
| DIMENSIONS (MM) | Length - 1790<br>Width - 61<br>Projection - 71 |
| CONSTRUCTION | Construction - Pressed steel<br>Construction 2 - & polycarbonate |
| CLASS | I |
| IP RATING | IP20 |
| WATTAGE (W) | 27/52 |
| LAMP TECHNOLOGY | LED |
| LUMENS (LM) | 3750/4170/4070, 6590/7520/7150 |
| LUMENS LIGHT SOURCE ONLY (LM) | 8410 |
| LUMEN TOLERANCE | 5% |
| EFFICACY (LM/W) | 165.5 |
| LUMENS EMERGENCY MODE (LM) | 310 |
| CIRCUIT WATTAGE (W) | 50.82 |
| CCT | 3000/4000/5700K |
| LIGHT COLOUR | CCT |
| CRI | >85 |
| SDCM | <6 |
| RUNNING CURRENT (A) | 0.223 |
| DISPLACEMENT FACTOR | >0.9 |
| SVM | 0 |
| PST-LM | 0 |
| BEAM ANGLE (DEGREES) | 145 |
| L70B50 LIFESPAN (HRS) | 60,000 |

**ML Accessories Ltd.** reserves the right to withdraw, improve, or modify any design without prior notification.
**ML Accessories Ltd.** cannot be held responsible for the incorrect application of any product.

| | |
|---|---|
| **DIMMABLE** | No |
| **EMERGENCY** | Maintained / Non-maintained / Switched |
| **SELF-TEST** | No |
| **OPERATING TEMPERATURE** | -5~50°C |
| **INPUT VOLTAGE** | 230V 50Hz |
| **CABLE GLAND INCLUDED** | No |
| **DRIVER** | DRIVER TYPE - Constant Current<br>MAX. OUTPUT - 26/52W<br>OUTPUT VOLTAGE - 30-43V<br>OUTPUT CURRENT - 600/1200mA<br>POWER FACTOR - 0.95<br>EFFICIENCY FULL LOAD - 96.8<br>ISOLATION - SELV<br>AMBIENT TEMPERATURE (Ta) - -20~50°C<br>CASE TEMPERATURE (Tc) - 75°C |
| **BATTERY INCLUDED** | Yes |
| **WARRANTY** | 5year(s) |
| **WARRANTY INFORMATION** | (excluding battery) |
| **ORIGIN OF MANUFACTURE** | China |
| **DECLARATION OF CONFORMITY (HELD ON FILE)** | Yes |
| **EAN** | 5056270881639 |

Date Created: 08/01/2024 21:25

**ML Accessories Ltd.** reserves the right to withdraw, improve, or modify any design without prior notification.
**ML Accessories Ltd.** cannot be held responsible for the incorrect application of any product.