

INSTALLATION & MAINTENANCE MANUAL MRBLED & MRBLED6



230V
50Hz



IP
20



RoHS
COMPLIANT



52

GENERAL INSTRUCTIONS

These instructions should be read carefully and retained after installation by the end user for future reference and maintenance

These instructions should be used to aid installation of the following products:

MRBLED / MRBLED6

This product is intended for installation in a “T” bar ceiling grid

SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS 7671) and current Building Regulations. If in any doubt, please consult a qualified electrician
- Please isolate mains prior to installation or maintenance
- Check the total load on the circuit (including when this luminaire is fitted) does not exceed the rating of the circuit cable, fuse or circuit breaker
- Be aware that these products may require an MCB upgrade to a type C due to high inrush currents
- This product is IP20
- This product is Class I and requires an earth
- This product is non-dimmable

INSTALLATION

Note: If this luminaire is being used in conjunction with a PIR sensor please confirm with the manufacturer of the sensors that they are compatible with LED products

- Provide power to the required point of installation
- Feed the mains cable through the entry point on the base of the luminaire
- Connect the Live (brown), Neutral (blue) and Earth (yellow and green) to the three-way push-fit terminal block
- Fit the luminaire into ceiling grid
- Connect the earth lead to the louvre and click the louvre into place
- Switch on and test for correct operation

WARNING

This product must be disconnected from the circuit if subjected to any high voltage or insulation resistance testing. Irreparable damage will occur if this instruction is not followed

The louvre is easily marked by handling, a protective glove is provided to prevent this

GENERAL

The LEDs fitted in this product are non-replaceable

This product should be recycled in the correct manner when it reaches the end of its life. Check local authorities for where facilities exist

Clean with a soft dry cloth only, do not use aggressive cleaning products or solvents which may damage the fitting

WARRANTY

This product has a warranty of 5 years from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations (BS7671), improper use, or removal of the batch codes will invalidate the warranty. If this product should fail within its warranty period it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

Knightsbridge[®]

the mark of quality



ML Accessories Limited
LU5 4LT
www.mlaccessories.co.uk

DCOCT18_V1