REX Slim | 20W

FEATURES AND USES

- ▲ Ideal for residential applications such as houses, driveways, patios, car parks and garages
- ▲ Suitable replacement for 200W halogen floodlight
- ▲ Made from die-cast aluminium and toughened glass
- ▲ Angled bracket for easy installation
- ▲ Supplied with 0.5m of power flex
- Available in black



REX Slim | 20W PIR

FEATURES AND USES

- ▲ Ideal for residential applications such as houses, driveways, patios, car parks and garages
- ▲ Suitable replacement for 200W halogen floodlight
- ▲ PIR with manual override
- ▲ PIR adjustable settings: lux, time and sensitivity
- ▲ PIR detection range of up to 10 metres

▲ IP65 PIR

- ▲ Made from die-cast aluminium and toughened glass
- ▲ Angled bracket for easy installation
 - ▲ Supplied with 0.5m of power flex
 - Available in black





K@

D

28



| Product Code | Wattage | Lumen Output | IK Rating | IP Rating | ССТ (К) | Colour Temp | Voltage | Beam Angle | Rated Life |
|-----------------|---------|-----------------|-----------|-----------|---------|----------------|-------------------------|-------------|------------|
| N6320 | 20W | 1800lm | IK07 | IP65 | 4000K | Cool White | AC220V-240V/ 50-60Hz | 110° | 30,000hrs |

