

# B.E.G. LUXOMAT®

## PD2-M-1C-SM/-FC/-FM



FC





## *i* PRODUCT INFORMATION

- Occupancy detector with potential-free contact
- Installation as Master
- One switching channel for operating the light
- Detection area can be extended with Slave units
- Push button manual switching available
- Additional functions can be set via optional remote control

### TECHNICAL DATA

110-240 V AC , 50 / 60 Hz

360°

Ø 10 m across

Ø 6 m towards

Ø d III loward

Ø 4 m seated

SM= IP20 FC= IP20 FM= IP20 / Class II

-25 °C to +50 °C

Housing UV- and shock resistant polycarbonate



IR-PD-1C, IR-PD-Mini

#### Channel 1

(control the lighting potential free)


2300 W,  $\cos \varphi = 1$ 


1150 VA,  $\cos \varphi = 0.5$ 

15 s - 30 min or pulse

(

10 - 2000 Lux





Description	Colour	Part number
PD2-M-1C-FC	white	92565
PD2-M-1C-SM	white	92550
PD2-M-1C-FM	white	92555
Accessory (optional)		
IR-PD-1C	grey	92520
IR-PD-Mini	grey	92159
Wire basket BSK (Ø 200 x 100)	white	92199
Socket IP54 for PD2- and PD4-SM	white	92161